

ADJ ELECTRAPIX BAR 16 - DMX TRAITS

CHANNEL											DMX VALUES	FUNCTION	
5 CH	6 CH	7 CH	9 CH	12 CH	13 CH	22 CH	24 CH	96 CH	99 CH	114 CH			
	1	1	1	1		1	1				0-255	All Red, 0~100%	
	2	2	2	2		2	2				0-255	All Green, 0~100%	
	3	3	3	3		3	3				0-255	All Blue, 0~100%	
	4	4	4	4		4	4				0-255	All Amber, 0~100%	
	5	5	5	5		5	5				0-255	All Lime, 0~100%	
	6	6	6	6		6	6				0-255	All UV, 0~100%	
								1	1	1	0-255	Red1, 0~100%	
								2	2	2	0-255	Green 1, 0~100%	
								3	3	3	0-255	Blue 1, 0~100%	
								4	4	4	0-255	Amber 1, 0~100%	
								5	5	5	0-255	Lime 1, 0~100%	
								6	6	6	0-255	UV 1, 0~100%	
								0-255	...	
								91	91	91	0-255	Red 16, 0~100%	
								92	92	92	0-255	Green 16, 0~100%	
								93	93	93	0-255	Blue 16, 0~100%	
								94	94	94	0-255	Amber 16, 0~100%	
								95	95	95	0-255	Lime 16, 0~100%	
								96	96	96	0-255	UV 16, 0~100%	
					1	7	7			97	0-255	RGBAL+UV Color Macros	
			7	7		8	8		97	98	0-255	Background Red, 0~100%	
			8	8		9	9		98	99	0-255	Background Green, 0~100%	
			9	9		10	10		99	100	0-255	Background Blue, 0~100%	
					2	11	11			101	0-255	RGB Background Color Macros	
1				10	3	12	12			102	0-255	Color Temperature 2300-9900K Linear, 0~100%	
													White Color Temperature Presets
2					4	13	13			103	0-22	Open	
											23-99	See WCT Preset Chart	
											100-255	No Function	
													Shutter, Strobe
											0-31	Led's Off	
											32-63	Led's On	
											64-95	Strobe effect slow to fast	
3				11	5	14	14			104	96-127	Led's On	
											128-159	Pulse-effect in sequences	
											160-191	Led's On	
											192-223	Random strobe effect slow to fast	
											224-255	Led's On	
4		7		12	6	15	15			105	0-255	Dimmer (Intensity), Intensity 0~100%	
5					7	16	16			106	0-255	Dimmer Fine (Intensity)	

ADJ ELECTRAPIX BAR 16 - DMX TRAITS

CHANNEL											DMX VALUES	FUNCTION	
5 CH	6 CH	7 CH	9 CH	12 CH	13 CH	22 CH	24 CH	96 CH	99 CH	114 CH			
											107		RGBAL+UV programs:
												0-10	Off
												11-26	Auto Program 1
												27-43	Auto Program 2
												44-60	Auto Program 3
												61-76	Auto Program 4
												77-93	Auto Program 5
					8	17	17					94-110	Auto Program 6
												111-126	Auto Program 7
												127-143	Auto Program 8
												144-160	Auto Program 9
												161-176	Auto Program 10
												177-193	Auto Program 11
												194-210	Auto Program 12
												211-226	Auto Program 13
											227-255	No Function	
					9	18	18				108	0-255	RGBAL+UV Programs Speed: Slow to Fast speed
					10	19	19				109	0-255	RGBAL+UV Programs Fade: Less to More
											110		RGB Background Programs:
												0-10	Off
												11-26	Auto Program 1
												27-43	Auto Program 2
												44-60	Auto Program 3
												61-76	Auto Program 4
												77-93	Auto Program 5
												94-110	Auto Program 6
												111-126	Auto Program 7
												127-143	Auto Program 8
												144-160	Auto Program 9
												161-176	Auto Program 10
												177-193	Auto Program 11
												194-210	Auto Program 12
												211-226	Auto Program 13
											227-255	No Function	
					12	21	21				111	0-255	RGB Background Programs Speed: Slow to Fast speed
					13	22	22				112	0-255	RGB Background Programs Fade: Less to More

ADJ ELECTRAPIX BAR 16 - DMX TRAITS

CHANNEL											DMX VALUES	FUNCTION
5 CH	6 CH	7 CH	9 CH	12 CH	13 CH	22 CH	24 CH	96 CH	99 CH	114 CH		
												Dim Mode
												000-020 Default to Unit Setting
												021-040 Standard
												041-060 Stage
												061-080 TV
												081-100 Architectural
												101-120 Theatre
												121-140 Stage 2
												Dim Speed
												141 0.1 s
												142 0.2 s
												143 0.3 s
												144 0.4 s
												145 0.5 s
											23	146 0.6 s
												147 0.7 s
												148 0.8 s
												149 0.9 s
												150 1 s
												151 1.5 s
												152 2 s
												153 3 s
												154 4 s
												155 5 s
												156 6 s
												157 7 s
												158 8 s
												159 9 s
												160 10 s
												161-255 Default to Unit Setting
												Dim Curves
												0-20 Square
												21-40 Linear
											24	41-60 Inv. Squa
												61-80 S. Curve
												81-255 No Function