

ELIMINATOR LP HEX 12 PLUS - DMX TRAITS

CHANNEL		DMX VALUES	FUNCTION
6Ch	10Ch		
	1	000-255	Total Dimmer , RGBWA+UV Total Dimmer- Dark to Bright
1	2	000-255	R Dimmer , Red Dimmer- Dark to Bright
2	3	000-255	G Dimmer , Green Dimmer- Dark to Bright
3	4	000-255	B Dimmer , Blue Dimmer- Dark to Bright
4	5	000-255	W Dimmer , White Dimmer- Dark to Bright
5	6	000-255	A Dimmer , Amber Dimmer- Dark to Bright
6	7	000-255	UV Dimmer , Ultraviolet Dimmer- Dark to Bright
	8		Strobe/Shutter
		000-031	Shutter Closed (LEDs OFF)
		032-063	Shutter OPEN (LEDS ON)
		064-095	Strobe effect slow to fast
		096-127	Shutter OPEN(LEDS ON)
		128-159	Pulse effect in sequences
		160-191	Shutter OPEN(LEDS ON)
		192-223	Random strobe effect slow to fast
		224-255	Shutter OPEN(LEDS ON)
	9		Function Choice
		000~050	CH1-CH8 Control.
		051~100	Different Colors output
		101~150	Colors Jump Change.
		151~200	Colors Gradate.
		201~250	Colors Pulse Change.
		251~255	Sound-Active
	10	000-255	Function/Speed , Slow to Fast (At the Colors output and sound choose the color)