

# ELIMINATOR MEGA PAR Z WASH - DMX TRAITS

Features subject to change without notice			
MODE/CHANNELS		VALUES	FUNCTION
10Ch	18Ch		
1	1		<b>Total Dimming</b>
		000 - 255	0% to 100%
2			<b>Red</b>
		000 - 255	Dark to light
3			<b>Green</b>
		000 - 255	Dark to light
4			<b>Blue</b>
		000 - 255	Dark to light
5			<b>White</b>
		000 - 255	Dark to light
	2		<b>Red1</b>
		000 - 255	Dark to light
	3		<b>Green1</b>
		000 - 255	Dark to light
	4		<b>Blue1</b>
		000 - 255	Dark to light
	5		<b>White1</b>
		000 - 255	Dark to light
	6		<b>Red2</b>
		000 - 255	Dark to light
	7		<b>Green2</b>
		000 - 255	Dark to light
	8		<b>Blue2</b>
		000 - 255	Dark to light
	9		<b>White2</b>
		000 - 255	Dark to light
	10		<b>Red3</b>
		000 - 255	Dark to light
	11		<b>Green3</b>
		000 - 255	Dark to light
	12		<b>Blue3</b>
		000 - 255	Dark to light
	13		<b>White3</b>
		000 - 255	Dark to light

# ELIMINATOR MEGA PAR Z WASH - DMX TRAITS

Features subject to change without notice			
MODE/CHANNELS		VALUES	FUNCTION
10Ch	18Ch		
6	14		<b>Shutter</b>
		000 - 031	Shutter Closed (LEDs Off)
		032 - 063	Shutter Open (LEDs On)
		064 - 095	Strobe Effect, slow to fast
		096 - 127	Shutter Open (LEDs On)
		128 - 159	Pulse Effect in Sequences
		160 - 191	Shutter Open (LEDs On)
		192 - 223	Random Strobe Effect, slow to fast
		224 - 255	Shutter Open (LEDs On)
7	15		<b>Zoom</b>
		000 - 255	Large to small spot size
8	16		<b>LED Macro Select</b>
		000 - 255	LED Macro Select, see LED Macros Chart
9	17		<b>LED Macro Speed</b>
		000 - 255	Slow to fast
10	18		<b>Reset</b>
		000 - 149	No Function
		150 - 255	Reset Focus Detection