

ELIMINATOR MEGA COLOR Q18 - DMX TRAITS

MODE/CHANNELS					VALUES	FUNCTION
4Ch	6Ch	9Ch	72Ch	74Ch		
1	1	1				All Red Dimmer
					000 - 255	0 - 100%
2	2	2				All Green Dimmer
					000 - 255	0 - 100%
3	3	3				All Blue Dimmer
					000 - 255	0 - 100%
4	4	4				All White Dimmer
					000 - 255	0 - 100%
			1	1		Red 1 Dimmer
					000 - 255	0 - 100%
			2	2		Green 1 Dimmer
					000 - 255	0 - 100%
			3	3		Blue 1 Dimmer
					000 - 255	0 - 100%
			4	4		White 1 Dimmer
					000 - 255	0 - 100%
			5	5		Red 2 Dimmer
					000 - 255	0 - 100%
			6	6		Green 2 Dimmer
					000 - 255	0 - 100%
			7	7		Blue 2 Dimmer
					000 - 255	0 - 100%
			8	8		White 2 Dimmer
					000 - 255	0 - 100%
			9	9		Red 3 Dimmer
					000 - 255	0 - 100%
			10	10		Green 3 Dimmer
					000 - 255	0 - 100%
			11	11		Blue 3 Dimmer
					000 - 255	0 - 100%
			12	12		White 3 Dimmer
					000 - 255	0 - 100%
			13	13		Red 4 Dimmer
					000 - 255	0 - 100%
			14	14		Green 4 Dimmer
					000 - 255	0 - 100%

ELIMINATOR MEGA COLOR Q18 - DMX TRAITS

MODE/CHANNELS					VALUES	FUNCTION
4Ch	6Ch	9Ch	72Ch	74Ch		
			15	15	000 - 255	Blue 4 Dimmer
						0 - 100%
			16	16	000 - 255	White 4 Dimmer
						0 - 100%
			17	17	000 - 255	Red 5 Dimmer
						0 - 100%
			18	18	000 - 255	Green 5 Dimmer
						0 - 100%
			19	19	000 - 255	Blue 5 Dimmer
						0 - 100%
			20	20	000 - 255	White 5 Dimmer
						0 - 100%
			21	21	000 - 255	Red 6 Dimmer
						0 - 100%
			22	22	000 - 255	Green 6 Dimmer
						0 - 100%
			23	23	000 - 255	Blue 6 Dimmer
						0 - 100%
			24	24	000 - 255	White 6 Dimmer
						0 - 100%
			25	25	000 - 255	Red 7 Dimmer
						0 - 100%
			26	26	000 - 255	Green 7 Dimmer
						0 - 100%
			27	27	000 - 255	Blue 7 Dimmer
						0 - 100%
			28	28	000 - 255	White 7 Dimmer
						0 - 100%
			29	29	000 - 255	Red 8 Dimmer
						0 - 100%
			30	30	000 - 255	Green 8 Dimmer
						0 - 100%
			31	31	000 - 255	Blue 8 Dimmer
						0 - 100%
			32	32	000 - 255	White 8 Dimmer
						0 - 100%

ELIMINATOR MEGA COLOR Q18 - DMX TRAITS

MODE/CHANNELS					VALUES	FUNCTION
4Ch	6Ch	9Ch	72Ch	74Ch		
			33	33	000 - 255	Red 9 Dimmer
						0 - 100%
			34	34	000 - 255	Green 9 Dimmer
						0 - 100%
			35	35	000 - 255	Blue 9 Dimmer
						0 - 100%
			36	36	000 - 255	White 9 Dimmer
						0 - 100%
			37	37	000 - 255	Red 10 Dimmer
						0 - 100%
			38	38	000 - 255	Green 10 Dimmer
						0 - 100%
			39	39	000 - 255	Blue 10 Dimmer
						0 - 100%
			40	40	000 - 255	White 10 Dimmer
						0 - 100%
			41	41	000 - 255	Red 11 Dimmer
						0 - 100%
			42	42	000 - 255	Green 11 Dimmer
						0 - 100%
			43	43	000 - 255	Blue 11 Dimmer
						0 - 100%
			44	44	000 - 255	White 11 Dimmer
						0 - 100%
			45	45	000 - 255	Red 12 Dimmer
						0 - 100%
			46	46	000 - 255	Green 12 Dimmer
						0 - 100%
			47	47	000 - 255	Blue 12 Dimmer
						0 - 100%
			48	48	000 - 255	White 12 Dimmer
						0 - 100%
			49	49	000 - 255	Red 13 Dimmer
						0 - 100%
			50	50	000 - 255	Green 13 Dimmer
						0 - 100%

ELIMINATOR MEGA COLOR Q18 - DMX TRAITS

MODE/CHANNELS					VALUES	FUNCTION
4Ch	6Ch	9Ch	72Ch	74Ch		
			51	51	000 - 255	Blue 13 Dimmer
						0 - 100%
			52	52	000 - 255	White 13 Dimmer
						0 - 100%
			53	53	000 - 255	Red 14 Dimmer
						0 - 100%
			54	54	000 - 255	Green 14 Dimmer
						0 - 100%
			55	55	000 - 255	Blue 14 Dimmer
						0 - 100%
			56	56	000 - 255	White 14 Dimmer
						0 - 100%
			57	57	000 - 255	Red 15 Dimmer
						0 - 100%
			58	58	000 - 255	Green 15 Dimmer
						0 - 100%
			59	59	000 - 255	Blue 15 Dimmer
						0 - 100%
			60	60	000 - 255	White 15 Dimmer
						0 - 100%
			61	61	000 - 255	Red 16 Dimmer
						0 - 100%
			62	62	000 - 255	Green 16 Dimmer
						0 - 100%
			63	63	000 - 255	Blue 16 Dimmer
						0 - 100%
			64	64	000 - 255	White 16 Dimmer
						0 - 100%
			65	65	000 - 255	Red 17 Dimmer
						0 - 100%
			66	66	000 - 255	Green 17 Dimmer
						0 - 100%
			67	67	000 - 255	Blue 17 Dimmer
						0 - 100%
			68	68	000 - 255	White 17 Dimmer
						0 - 100%

ELIMINATOR MEGA COLOR Q18 - DMX TRAITS

MODE/CHANNELS					VALUES	FUNCTION
4Ch	6Ch	9Ch	72Ch	74Ch		
			69	69		Red 18 Dimmer
					000 - 255	0 - 100%
			70	70		Green 18 Dimmer
					000 - 255	0 - 100%
			71	71		Blue 18 Dimmer
					000 - 255	0 - 100%
			72	72		White 18 Dimmer
					000 - 255	0 - 100%
	5	5		73		Shutter
					000 - 031	Shutter Closed (LEDs Off)
					032 - 063	Shutter Open (LEDs On)
					064 - 095	Strobe Effect, slow to fast
					096 - 127	Shutter Open (LEDs On)
					128 - 159	Pulse Effect in Sequences
					160 - 191	Shutter Open (LEDs On)
					192 - 223	Random Strobe Effect, slow to fast
					224 - 255	Shutter Open (LEDs On)
	6	6		74		Master Dimmer
					000 - 255	0 - 100%
		7				Effects
					000 - 009	Off
					010 - 019	Static Color, Ch8 Select (Red, Green, Blue, White, Yellow Purple, Cyan, RGBW)
					020 - 029	Pulsing Effect, Ch9 Select Color
					030 - 039	Color Jump Effect
					040 - 049	Gradient Change Effect
					050 - 059	Pulse Change Effect, Ch9 Select Color
					060 - 069	Autorun Effect 1, Ch9 Select Color (cycle autorun)
					070 - 079	Autorun Effect 2, Ch9 Select Color
					080 - 089	Autorun Effect 3, Ch9 Select Color
					090 - 099	Autorun Effect 4, Ch9 Select Color
					100 - 109	Autorun Effect 5, Ch9 Select Color
					110 - 119	Autorun Effect 6, Ch9 Select Color
					120 - 129	Autorun Effect 7, Ch9 Select Color
					130 - 139	Autorun Effect 8, Ch9 Select Color
					140 - 149	Autorun Effect 9, Ch9 Select Color

ELIMINATOR MEGA COLOR Q18 - DMX TRAITS

MODE/CHANNELS					VALUES	FUNCTION
4Ch	6Ch	9Ch	72Ch	74Ch		
		7				Effects (continued)
					150 - 159	Autorun Effect 10, Ch9 Select Color
					160 - 169	Autorun Effect 11, Ch9 Select Color
					170 - 179	Autorun Effect 12, Ch9 Select Color
					180 - 189	Autorun Effect 13, Ch9 Select Color
					190 - 199	Autorun Effect 14, Ch9 Select Color
					200 - 209	Autorun Effect 15, Ch9 Select Color
					210 - 229	Autorun Effect 16, Ch9 Select Color
					230 - 233	Sound Mode 1, Ch9 Select Color
					234 - 237	Sound Mode 2, Ch9 Select Color
					238 - 241	Sound Mode 3, Ch9 Select Color
					242 - 245	Sound Mode 4, Ch9 Select Color
					246 - 249	Sound Mode 5, Ch9 Select Color
					250 - 255	Sound Mode 6, Ch9 Select Color
		8				Effects Adjustment
					000 - 255	When Effect channel is set to Static color mode: no function When Effect channel is set to Autorun Effect: speed adjustment, slow to fast When Effect channel is set to Sound Mode: sensitivity adjustment, least to most sensitive
		9				Color
					000 - 031	Default Color
					032 - 063	Red, Ch7 Manual Color Selection
					064 - 095	Green, Ch7 Manual Color Selection
					096 - 127	Blue, Ch7 Manual Color Selection
					128 - 159	Yellow, Ch7 Manual Color Selection
					160 - 191	Purple, Ch7 Manual Color Selection
					192 - 223	Cyan, Ch7 Manual Color Selection
				224 - 255	White, Ch7 Manual Color Selection	